

## Cascadable Multiswitch 2 in 6

SMK 2261 F



For 6 subscribers.

- Remote powered by satellite receiver
- Cascadable multiswitch taps or 6 subscriber each. The IF polarity selection is controlled by the remote voltage, < 14 V  $\cong$  vert. / > 16 V  $\cong$  hor. provided by the receiver

Model Art. No.	SMK 2261 F 842343
EAN	4040326423431
Frequency range	2x47 ... 2200 MHz
Inputs / outputs SAT / terrestrial	2 / 2
Outputs / subscribers	6
Through loss terrestrial	0 ... 2 dB
Through loss SAT IF	3 ... 4 dB
Tap loss terrestrial	37 ... 14 dB
Tap loss SAT	17 dB
Isolation Trunkline / trunkline terrestrial	$\geq 45$ dB
Isolation Trunkline / trunkline SAT	$\geq 33$ dB
DC-pass max. Trunkline 0; 2; 3 und 4	1 A
Ambient temperature	-20 ... +50 °C
Dimensions (mm)	145 x 130 x 39

**!** Only useable in combination with launch amplifier SBK 3203 NF

## Cascadable Multiswitch 2 in 12

SMS 2212 F



For 12 subscribers.

- Remote powered by satellite receiver
- The IF polarity selection is controlled by the remote voltage, < 14 V  $\cong$  vert. / > 16 V  $\cong$  hor. provided by the receiver

Model Art. No.	SMS 2212 F 842344
EAN	4040326423448
Inputs / outputs	2 / 2
Outputs / subscribers	12
Through loss: SAT IF: 950 ... 2200 MHz	0 dB
Tap loss: SAT	0 dB
35 dB IMA <sub>2</sub> / EN 60728-3	86 dB $\mu$ V
35 dB IMA <sub>3</sub> / EN 60728-3	94 dB $\mu$ V
Isolation Receiver / receiver	$\geq 23$ dB
Isolation Trunkline / trunkline	$\geq 30$ dB
Noise figure	7 dB
Current consumption	75 mA
Capacity (IF ports) max.	500 mA
Ambient temperature	-20 ... +50 °C
Dimensions (mm)	145 x 130 x 39

SAT IF