

TV EXPERT Terrestrial Meter

Part# ROVER-TVEXPERT



Automatically Stores all channels of your city, checks the best antenna pointing and analyzes the result of your work by measuring the quality and power up-to 140 channels in blocks of 8 channels.

KEY FEATURES

- High precision with all channels calibrated
- Worldwide TV standards
- Up to 140 chs analysis in blocks of 8 digital and/or analog channels
- Fast quality meas.: fail-marg.-pass
- Li-PO long battery duration
- Robust metal housing



MEASUREMENTS & SPECTRUM ANALYSIS

- Frequency Range: 44 MHz to 880 MHz.
- Input Impedance: 75 ohm (interchangeable "F" connector).
- Power range MEASURE 10 to 100 dB μ V
- Fast spectrum with MAX HOLD: Full spectrum capabilities with peak memory, variable span and automatic reference level.
- Measures: All digital and analog signals.
- Quality FAIL - MARGINAL - PASS: Measuring the quality and the power up-to 140 CHs in blocks of 8 Digital or Analog channels simultaneously.
- Barscan: TV analog and digital bars scan from 10 to 100 channels.
- Memory plan: World Wide countries with related channels plans are pre-memorized.

GENERAL SPECIFICATIONS

- DC voltage at RF input: 5Vdc.
- Battery: Rechargeable Li-Po battery pack, 5 hour duration.
- USB Micro: For battery charge and PC interface for SW up-grade and memory plan management.
- Housing: Metal box and rain proof bag.
- Size: H 95 x W 160 x D 34 mm (meter only).
- Weight: 500 gr.

* USB CHARGER NOT INCLUDED (5VDC - 1A)